

The most easy phones to use on Liberty PCS-M network is Metro PCS phones
In order to activate a Metro PCS phone you must be a registered member with Liberty.
In order to register as a Liberty member you must be referred by an existing Liberty member

How to Reprogram a MetroPCS Phone to work on Liberty PCS-M network?

In order to activate the service make 1 phone call to our Tech Support
(760)756-5000 for English or Spanish

Monday-Friday hours are from 8am-7pm Pacific Time (11am-10pm Eastern Time)

Saturday 9am-1pm on Pacific Time (12pm-4pm Eastern Time)

They will add the cell phone service to your account and prorate the cost of the service
if you do not have 3 referrals with the same exact service at the time of activation.

[you can not transfer a number to this service - you will be given a new number]

As soon as Tech Support assign you your new cell phone number
base on your local zip code or your request - Your account is active.

You will need to make sure you are also getting your "MIN" number(Mobile Identification Number)

Your temporary mail box code will be **9999**

Most phones can be programed over the air(OTA) just by entering *228 or *22890 + "send"

If your phone is still not working you have 2 options:

A- Go to a local Metro PCS store(corporate store is better) and they can make it work

B- You can manually program it by yourself

How to do it by yourself?

- 1)** Click on Menu then "Settings and press "*" or press 11111
select options from the bottom of the screen.
Select the "NAM" option.
Most phones come with the option to select either NAM1 or NAM2.
Enter the SPC code [the security code(SPC) for all metro phones is **587846**]
- 2)** Highlight or click on "MDN" or begin typing the MDN if the screen displays with only that option.
For touch screen models, touch the box under "Edit MDN," (MDN=Mobile Device Number)
then enter the MDN which is your new cell phone number that you got from Liberty.
- 3)** Highlight or click on "MIN" or begin typing your MIN if the screen displays with only that option.
For touch screen models, touch the box under "Edit MIN,"
then enter the MIN that Liberty Tech Support provided you.
- 4)** Highlight or click on "Home SID" or touch the box under "Edit Home SID"
and enter the SID number **6503** (System Identification Number)
[in most cases it will be there so you will not need to enter it - it is the same for all users]
- 5)** Click "Save" or "Done," and, if the phone does not turn off or reset,
click the "End" button, which is the red phone symbol.
[if the phone is not working - you will need to turn the phone off, remove the battery,
wait for a minute, put it back and turn the phone back on - that should do it]